

2299UCJ-214

Nimi: **Moottorinsäädin**
Moottorisäädin 0,1–1A
Jussi

Tyyppi: 2299UCJ-214
EAN: 6410035127551
Snro: 3512755



Kuvaus: Puhallinmoottoreiden kierrosluvun säätöön. Toimitetaan varustettuna keskiölevyllä, peitelevyllä, hohtolampulla ja varasulakkeella. Nimellisjännite: 230 V, 50 Hz.

Pakkaus: 1/10
Yksikkö: KPL



Tekniset tiedot

Mitat

Mitat 85x85x56
Paino 126 g

Luokat

Kotelointiluokka IP20

Sähkösuureet

Nimellisvirta 0.1 ... 1 A
Nimellisjännite 230 V

Elektroniikka

Sulake F 1 A
Käyttötaajuus 50 Hz
Soveltuvuus Puhallinmoottoreiden kierrosluvun säätöön

Värit

Väri Valkoinen

ETIM

ETIM 7 EC000256 (EC000256)
ETIM 8 EC000256 (EC000256)

ETIM 7

Mounting method Flush mounted (plaster)
Colour White
RAL-number 9010
Nominal current 1 A

2299UCJ-214

Output voltage	230 V
Number of phases	1
Power control step less	yes
Basic element without cover	no
Method of operation	Turn button
Illumination	Illuminated (on)
Switching contact	no
With temperature sensor	no
Height	81 mm
Width	81 mm
Depth	55 mm
Degree of protection (IP)	IP20